

Distributed by:



www.Jameco.com ♦ 1-800-831-4242

The content and copyrights of the attached
material are the property of its owner.

2-Port Serial ISA I/O Card

16C550 UART (16 Byte FIFO)

Hardware Guide

Introduction Jameco Part Number 171555

This hardware guide is a supplement to your ISA User's Guide and is designed to provide users with quick and easy ISA I/O card installation instructions. Please read your ISA I/O card User's Guide first before referring to this Hardware Guide.

Hardware Specifications

Your ISA serial port card has the following hardware specifications:

- Two High Speed RS232 Serial Ports For Use with External Modems, Graphics Tablets, Mice or Other Serial Peripherals
- 16-bit ISA Interface
- Compatible With All IBM PC/AT and AT Compatible Computers
- 16C550 UART Technology for High Speed Serial Communications of up to 921 KB/s
- COMs 1-12 and IRQs 3-15
- 16 Byte FIFO Buffers on Both Transmit and Receive

Technical Specifications

- Computer Compatibility: 486/586/Pentium/Pentium II/III
- Operating System Compatibility: Win 95, 98, NT, 2000, Linux
- RS-232 Interface
- Serial Connector: 2 x 9-Pin D-Sub Male